

Miniature 315MHz 1-Channel RF Receivers & Transmitters

SK-910RAQ 1-Channel Receiver – 3Amp Relay Output

SK-910RAVQ 1-Channel Receiver – Transistor Group O/P

- Four programmable output modes:
 - 4-Second Momentary Output
 - Validity Output
 - Toggle Output
 - 1-Second Momentary Output
- Flexible operating voltage: SK-910RAQ: 11-24 VAC/VDC
SK-910RAVQ: 3-13.8 VDC
- Up to 500ft (152m) range*, 315MHz
- Controls garage doors, gates, house lights, alarm panels, or other devices via remote
- Compatible with all 315MHz SECO-LARM transmitters (fixed code and CODEBUMP™)
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode



SK-910RAQ



SK-919TD1S-UPQ

SK-919TD1S-UPQ Factory Pre-Coded Transmitter

SK-919TT1S-BU DIP-Switch-Coded Transmitter

- Operates up to 500ft (152m)*, 315MHz
- LED transmission indicator
- Includes 12VDC alkaline battery
- Compatible with all 315MHz SECO-LARM receivers
- SK-919TD1S-UPQ: Over 68 billion possible codes
- SK-919TT1S-BU: Use for “block coding” a large number of transmitters with the same code, or for simple matching of a transmitter already in use



SK-919TP1H-BUQ

SK-919TP1H-BUQ 1-Button Handheld Transmitter

- Operates up to 500ft (152m)*, 315MHz
- Over 68 billion (6.8x10¹⁰) possible codes
- Includes two 3VDC lithium batteries
- Visor clip and belt clip included. Belt-clip holster & wall-mount bracket also available (Model: SK-9HBC)
- Slimline design
- Low battery indicator – LED flashes when battery drops below 2VDC
- Compatible with all 315MHz SECO-LARM receivers

SK-910RAQ and SK-910RAVQ Specifications:

Model	SK-910RAQ	SK-910RAVQ
Range	Up to 500' (150m) in open air	
Operating voltage	11-24 VAC/VDC	3-13.8 VDC
Current Draw	5mA Standby, 50mA LED flashing @ 12VDC	5mA Standby, 15mA LED flashing @ 12VDC
Output Mode	Programmable 4-sec momentary (default), 1-sec momentary, toggle (ON/OFF), validity	
# of outputs	1	1
Output Type	3A Relay (NO/NC/COM)	5A Transistor GND
Transmitter	Compatible with all 315MHz SECO-LARM transmitters	

*Actual range may vary greatly depending on the installation and operating environment.