



5806W3

Wireless Photoelectric Smoke Detector

The Honeywell Home 5806W3 is a 3V battery operated, photoelectric smoke detector with a built-in wireless transmitter. It facilitates fire verification for false alarm reduction requirements by ANSI/SIA CP-01 standards and is intended for use with any of the Honeywell Home 5800 Series wireless receiver/transceivers for residential installations. The 5881ENHC or 5883H receivers are required for commercial installations.

The transmitter can send alarm, tamper, maintenance (when control panels are equipped to process maintenance signals) and battery condition messages to the system's receiver. The maintenance signal fully complies with the sensitivity test requirement specified in NFPA 72, 7-2.2 and is UL approved.

The 5806W3 incorporates a state-of-the-art optical sensing chamber and advanced microprocessor. It also helps eliminate nuisance alarms and virtually eliminates non-billable service calls and fines resulting from false alarms. The microprocessor allows the detector to automatically maintain proper operation at factory calibrated detection levels, even when sensitivity is altered due to the presence of contaminants settling into the unit's smoke chamber. A removable detector cover and chamber top allows the technician to quickly and easily clean the detector chamber without disassembling the detector head.

Since there are no holes to drill or wires to run, installers can preserve the beauty of the protected premise while protecting it. The 5806W3 is an ideal smoke detector for difficult to wire locations, applications where room aesthetics are critical or where hazardous materials exist.



FEATURES AND BENEFITS

- **Smoothing Algorithms:** Mathematical calculations in the detector's software that minimize nuisance alarms by smoothing out short term spikes from dust and smoke.
- **Smart Check:** A signal is sent to the control panel when the detector requires cleaning. This allows a regular, non-emergency service call to clean the detector before it goes into alarm.
- **Drift Compensation:** Virtually eliminates nuisance alarms from long-term dust build-up by automatically adjusting the detector's sensitivity.
- **Removable Detector Cover and Chamber Top:** Provides the technician the ability to quickly and easily clean the detector chamber without disassembling the detector head.
- **Approved UL Listings for Residential and Commercial Applications:** Both residential and commercial installation requirements are met.
- **Additional LED Status Indicators:** Identifying between alarm or trouble conditions is easier with green and red LED status indicators. The green LED denotes a normal condition while the red LED indicates an abnormal condition.
- **Easy-to-install Mounting Base:** The sturdy mounting base allows the detector to be more easily installed on uneven surfaces (i.e. stucco). The mounting base has larger mounting ports to accommodate drywall anchors for easy surface mounting.
- **Improved Robust RF Field Strength:** The distance between the detector and receiver has been significantly increased.
- **Additional Features:**
 - Utilizes one long-life 3V lithium battery
 - Microcontroller runs on an 4.0 MHz clock
 - Horn operates at 3.3 KHz with sound pressure level of 85dBA at 10 feet
 - Built-in wireless transmitter, temporal code 3 sounder

5806W3 Technical Specifications

Dimensions: Diameter: 5.3", Height: 2.30"

Weight: 8.5 oz. (without batteries)

Operating Temperature: 32–100°F (0–37.8°C)

Humidity Range: 0% to 95% RH, non-condensing

Air Velocity: 1,000 ft./min. max.

Operating Voltage: 2.5–3.6VDC

Standby Current: 8.5 A avg.

Alarm Current: 35 mA max.

Power Source: One 3V CR123A lithium Battery†

Audible Output: 85dB min. @ 10 ft.

Agency Listings: UL268 – Commercial and Residential

* With adapter bracket (4.9" without mounting base)

† Replacement batteries include Duracell DL123A, Sanyo CR123A, Panasonic CR123A, or ADEMCO 466

ACCESSORIES (SOLD SEPARATELY)

SENS-RDR Infrared Sensitivity Reader

Reduces testing time, simplifies sensitivity measurements and displays them precisely in terms of percent per foot obscuration. The SENS-RDR eliminates the need for magnets, voltmeters and ladders.



RT Removal Tool

Simplifies the attachment and removal of the detector head to the mounting base. It may be attached to a threaded extension pole or broom handle thereby eliminating the need for ladders.



ORDERING

5806W3	Wireless Photoelectric Smoke Detector with Built-in Wireless Transmitter
Accessories sold separately:	
SENS-RDR	Hand-held Sensitivity Reader
RT	i3 Removal Tool used for easy installation and removal of head from base

For more information

security.honeywellhome.com/hsc



Resideo Technologies, Inc.

2 Corporate Center Drive, Suite 100
P.O. Box 9040
Melville, NY 11747
1-800-645-7492
resideo.com

L/5806W3DS/D | 06/19
© 2019 Resideo Technologies, Inc.
This product is manufactured by Resideo and its affiliates. The Honeywell Home trademark is used under license from Honeywell International Inc. All rights reserved.

Honeywell Home